

**L.EEC025 - FUNDAMENTALS OF SIGNAL PROCESSING**

*Academic year 2024-2025, week 3  
TP (Recitation) problems*

**Topics:** Frequency response of an LTI system, DTFT properties

**Problem 1**

A discrete system is described by the difference equation  $y[n] = \frac{1}{5} \sum_{k=0}^{k=4} x[n-k]$  and it is admitted that the system starts from rest.

Create a .m Matlab command file that implements the following operations:

- creates a line vector  $h$  consisting of the impulse response of the system and represents it graphically (using the `stem` command), adding also a title and labels to the XX and YY axes,
- finds and represents in figure 2 the absolute value of the frequency response of the system in the frequency range  $0-2\pi$ , and using  $N=512$  points for the representation (in order to facilitate the readability of the XX axis, normalize its representation by  $\pi$ ),
- finds and represents in figure 3 the phase response of the system in the frequency range  $0-2\pi$ , and using  $N=512$  points for the representation (in order to facilitate the readability of the XX axis, normalize its representation by  $\pi$ ).

**Problem 2**

An averaging filter has the following difference equation:

$$y[n] = \frac{1}{5} (x[n] + x[n-1] + x[n-2] + x[n-3] + x[n-4]).$$

- a) Find its impulse response,  $h[n]$ .
- b) Find its frequency response,  $H(e^{j\omega})$ , and represent its absolute value and phase.

**Problem 3**

Consider that  $x[n]$  is a real-valued and causal discrete-time signal, and its Fourier transform is  $X(e^{j\omega})$ . If  $X_R(e^{j\omega}) = 1 + \cos(\omega)$  is the real part of  $X(e^{j\omega})$ , find  $X_I(e^{j\omega})$ , the imaginary part of  $X(e^{j\omega})$ .